



INSTALACIÓN

1. Pasar los cables por el agujero de la tapa posterior (A).

2. Sujetar la placa (A) al techo con los tornillos (B).

3. Pasar el cable por el florón y fijar con sujetacables

4. Conecte los cables de la luminaria al driver (SEC + -).

**TENER EN CUENTA LA POLARIDAD DE LOS CABLES! (CABLE ROJO, +) (CABLE NEGRO, -)
TAL COMO LO INDICA LA CAJA DE CONEXIONES C.**

5. En caso de error no se encendera la lampara, revertir la conexión de los cables del paso 3.

6. Conectar cables de alimentación al driver (PRI)

**ATENCIÓN! SI EL CABLE DE ALIMENTACION NO SE CONECTA EN LA ENTRADA
CORRECTA (PRI), VA A FUNDIR EL DRIVER.**

7. Sujetar el florón (D) con la placa (A) a través de los tornillos.

INSTALLATION

1. Thread the electrical mains through the hole in the backplate (A).

2. Secure the backplate (A) to the roof with the screws (B).

3. Pass the cable through canopy and fix it with cord grip.

4. Connect the electrical mains in the driver (SEC + -)

**KEEP IN MIND POLARITY OF THE WIRES! (RED WIRE, +) (BLACK WIRE, -), AS MARKED
IN THE DRIVER C.**

5. If there is an error the lamp will not light up, reverse de cable connection from step 3.

6. Connect the power cord in the driver (PRI)

**ATTENTION! IF THE POWER CORD IS NOT CONNECTED ITO THE CORRECT INPUT
(PRI), IT WILL BURN OUT THE DRIVER.**

7. Secure the assembly (D) with the backplate (A) with screws.